

BT201

Non-contact AC voltage detector with visual and sound alert



Features:

- Detect AC voltage in outlets, lighting fixtures, switches circuit breakers, wire, and cables.
- Detect live wire
- Locate wire break point.
- Safe, non-contact design.
- Detect 50-600V AC voltage
- Bright LED and sound alert if voltage detected.
- Conforms to EN61010-1 CATIV 600V CE-EMC & LVD

General Specifications

Indicator	: RED bright LED and audible beeper
Voltage Range	: AC 50V to 600V
Frequency Range	: 50Hz to 60Hz
Power	: 2 batteries x 1.5V IEC LR3 AAA or equivalent.
Battery Life	: Typical 24 hours
Dimension	: 25 (W) x 150 (H) x 25 (D) mm.
Weight	: Approx. 60 g (including battery).



BST Caltek Industrial Ltd.

www.bstcaltek.com
www.htcaltek.com

www.caltek.com.hk
www.finestcaltek.asia

Flat G, 2/F., Block 4, Golden Dragon Industrial Centre, 182-190 Tai Lin Pai Road, Kwai Chung, N.T., Hong Kong
E-MAIL: sales@caltek.com.hk TEL: (852) 2401-1222 FAX: (852) 2420-3472